



Mobile: +86-139-2528-0716





SPECIFICATION FOR LCD MODULE

MODULE NO: PV10103TD40D-C Doc.Version:01

L	ustomer Approval	l :		
	☐ Accept			☐ Reject
				,
	KINGTECH	NAME	SIGNATURE	DATE
	Prepare	Electronic Engineer		
	Check	Mechanical Engineer		
	Verify			
	Approval			

- **APPROVAL FOR SPECIFICATIONS ONLY**
- APPROVAL FOR SPECIFICATIONS AND SAMPLE



E-mail: Helen@kingtechgroup.cn

TEL: 86-755- 23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn




1. Revision History

Sample Version	DOC. Version	DATE		DESCRIPTION	CHANGED BY
A0	00	2019-9-4	FULL SPEC	First issue	Yangrongwu
A1	01	2020-3-12		Update drawing	xiao










2. Table of Contents:

NO	CONTENTS	PAGE				
1	Revision History	1				
2	Table of Contents					
3	General Specification	4				
4	LCM drawing	5				
5	Electrical Characteristics	6				
6	Optical Characteristics	9				
7	Interface Pin Assignment	13				
8	Backlight	15				
9	Packing	16				
10	Standard Specification for Reliability	17				
11	Specification of Quality Assurance	19				
12	Handing Precaution	27				





Mobile: +86-139-2528-0716





3. General Specification:

ITEM	CONTENTS			
Module Size	171.8(W) * 255.8(H) * 3.95(T) mm			
Display Size(Diagonal)	10.1 inch			
Display Format	1200* 1920 Pixels			
Active Area	135.36(W) *216.58(H) mm			
Pixel Pitch	37.6 (W)x 112.8(H) um			
LCD Type	TFT/ Normally BLACK			
View Angle	ALL			
Drive IC	HX8279D			
Weight	TBD			




E-mail: Helen@kingtechgroup.cn TEL

TEL: 86-755-23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn







E-mail: Helen@kingtechgroup.cn

TEL: 86-755-23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn



5. Electrical Characteristics

5-1 Absolute Maximum Ratings

$(Ta=25^{\circ}C\ VSS=0V)$

Item	Symbol	Min.	Type	Max.	Unit	Remark
Input Voltage	V _{CI} -V _{SS}	-0.3	-	+3.9	Volt	Note1
Supply Voltage	V _{DDIO} -V _{SS}	-0.3	-	+3.6	Volt	Note1
Operating Temperature	Topr	-10	-	+50	°C	-
Storage Temperature	Tstg	-20	-	+60	°C	-

Note1: Absolute maximum rating is the limit value beyond which the IC maybe broken. They do not assure operations.

5-2 Operating Conditions

(VDD=2.8 ~ 3.3V,	(VDD=2.8 ~ 3.3V, T _A =-40 ~ 85 °C)									
Parameter	Symbol	Test condition		Spec.		Unit	Note			
rarameter	Syllibol	rest condition	Min.	Тур.	Max.	Offic	NOLE			
Input high voltage	V_{IH}	VDD= 2.8 ~ 3.3V	$0.7 V_{DD1}$	-	VDD1	V	-			
Input low voltage	V_{IL}		0	ı	$0.3 V_{DD1}$	V	•			
VPP	V _{IH} V _{IL}	VPP	0.8	8.25	8.5	V	(1)			
Output high voltage (SDO, CABC_PWM_OUT)	V _{OH1}	I _{OH} = -1.0 mA	0.8 V _{DD1}	-	VDD1	V	-			
Output low voltage (SDO, CABC_PWM_OUT)	V_{OL1}	VDD= 1.7 ~ 2.0V I _{OL} = 1.0 mA	0	-	0.2 V _{DD1}	V	-			
-	ı	VSYNC, HSYNC	-	-	1	uA	-			
Logic High level input current	I _{IH}	RESX, DCX, CSX, SCL	-	ı	1		•			
Logic i ligit level li put current	I _{IHD}	DB[23:0], SDI, DCX	•	ı	1	uA	ı			
		DB[23:0]	-	-	1					
Logic Low level input current	I _{IL}	VSYNC, HSYNC	-1	ı	-	uA	ı			
		RESX, DCX, CSX, SCL	-1	-	-		-			
Logic Low level input current	I_{ILD}	DB[23:0], SDI, DCX	-1	-	-	uA				
		DB[23:0]	-1	-	-		1			
Current consumption standby mode (VDD3-VSSA)	I _{ST(VDD)}		-		TBD	μΑ	-			
Current consumption standby mode (VDD1- VSSD)	I _{ST(VDD1)}	VDD3/HS_VCC=2.8V, VDD1=1.8V $T_A = 25$ °C	-		TBD	μА	-			
Current consumption standby mode which include HS_VCC (HS_VCC-HS_VSS)	I _{ST(VDD1)}	(DSI Ultra Low Power mode)	-		TBD	μА	-			
Oscillator tolerance	△ OSC	T _A =25°C	-5	-	5	%	-			



5-3 TIMING CHARACTERISTICS

13.1 MIPI AC characteristics




Figure 13.1: Switching the clock lane between clock transmission and low-power mode




Figure 13.2: Timing of high-speed data transmission in bursts




Figure 13.3: Tumaround Procedure

E-mail: Helen@kingtechgroup.cn TEL:

TEL: 86-755- 23037763

Mobile: +86-139-2528-0716



Web: www.kingtechgroup.cn

13.2 MIPI data-clock timing specification




Figure 13.4: Data to clock timing

Downward to	Prombal	-1	11mm		
Parameter	Symbol	Min.	Typ.	Max.	Unit
Ul instantaneous	Ulinst	1.0	-	12.5(1)	ns
Data to clock setup time	Tserue	0.3	0.7		UIINST
Data to clock hold time	THOLD	0.3	8-0	-	UINST

Note: (1) This value corresponds to a minimum 80 Mbps data rate.



E-mail: Helen@kingtechgroup.cn

TEL: 86-755- 23037763

Mobile: +86-139-2528-0716







6. Optical Characteristics: 6. OPTICAL SPECIFICATION

Item		Symbol	Conditions	S	pedficatio	ns	Unit	Note
		Зуппоог	CONTINUE	Min.	Тур.	Max.	Onc	Note
Transmittance (w/o APCF)		T%	Vlewing	3.53%	4.04%		%	All left side data are based on INX's following condition –
Contrast R	atto	CR	normal angle θ _x = θ _y =0"	800	1000		-	1.LC : AAS . 2.CF : CG 70% CF.
Response 1	Time	T _{on+} T _{off}	S. 57 5		25		ms	3.Light Source : INX LED BLU. 4.Polarizer :
	Hor.	θ _{X+}		80	85			CF:SRW062APN1LT4 TFT:SRW062AWL2/APFV3
vlewing Angle	TRA.	θ _χ .		80	85		deg.	5.Machine : DMS 803, (ConoScope for View Angle). 6. VLC dark ≤ 0.3 V, VLC
	Ver.	θ _{y+}		80	85		,	white ≥ 4.1 V
		θγ.		80	85			7.Back light structure: Diffuser+BEF+BEF+ Diffuse
	Red R	Pox		0.631	0.651	0.671	-	
	NEW	Ry		0.311	0.331	0.351	-	
	Green	Gx		0.255	0.275	0.295	-	
CF only Color	Oreen	Gy	Viewing	0.54	0.56	0.58		
Chromaticity	Blue	Bx	normal angle	0.12	0.14	0.16	-	Under C light Simulation
(CIE 1931)	Lilue	Ву	θ _X = θ _Y =0"	0.075	0.095	0.115	-	
	White	Wx		0.28 0.3 0.32 -				
	AAIIIIG	Wy		0.305	0.325	0.345	-	
	Color	Gamut			65]

INX LED BLU Spectrum: "Note(1)





E-mail: Helen@kingtechgroup.cn TEL: 86-755- 23037763

Mobile: +86-139-2528-0716



Web: www.kingtechgroup.cn

*Note (2) Definition of Contrast Ratio (CR):

The contrast ratio can be calculated by the following expression.

Contrast Ratio (CR) = L63 / L0


L63: Luminance of gray level 63

L 0: Luminance of gray level 0

CR = CR(5)

CR (X) is corresponding to the Contrast Ratio of the point X at Figure in Note (5).

*Note (3) Definition of Response Time (Ton, Toff):



E-mail: Helen@kingtechgroup.cn


TEL: 86-755- 23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn




*Note(4) Definition of Viewing Angle



*Note (5) Measurement Set-Up:

The LCD module should be stabilized at a given temperature for 20 minutes to avoid abrupt temperature change during measuring. In order to stabilize the luminance, the measurement should be executed after lighting Backlight for 20 minutes in a windless room.





E-mail: Helen@kingtechgroup.cn


TEL: 86-755-23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn



*Note (6)







TEL: 86-755- 23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn



7. Interface Pin Assignment:

7-1 LCM FPC Interface

<u>-1 LCM </u>	FPC Interface		
Pin NO.	Symbol	Level	Remark
1	NC	/	/
2	VDD3.3V	Н	A supply voltage 3.3V
3	VDD1.8V	Н	A supply voltage 1.8V
4	GND	L	Ground
5	/RESET(1.8V)	H/L	Reset pin
6	NC	/	/
7	GND	L	Ground
8	D0_N	H/L	MIPI_DP0- are differential data signal line
9	D0_P	H/L	MIPI_DP0+ are differential data signal line
10	GND	L	Ground
11	D1_N	H/L	MIPI_DP1- are differential data signal line
12	D1_P	H/L	MIPI_DP1+ are differential data signal line
13	GND	L	Ground
14	CLK_N	H/L	CLOCK Lane negative-end input pin
15	CLK_P	H/L	CLOCK Lane positive-end input pin
16	GND	L	Ground
17	D2_N	H/L	MIPI_DP2- are differential data signal line
18	D2_P	H/L	MIPI_DP2+ are differential data signal line
19	GND	L	Ground
20	D3_N	H/L	MIPI_DP3- are differential data signal line
21	D3_P	H/L	MIPI_DP3+ are differential data signal line
22	GND	L	Ground
23	NC	/	/
24	NC	/	/
25	GND	L	Ground
26~29	NC	/	/
30	GND	L	Ground
31	LEDK	L	Backlight Cathode
32	LEDK	L	Backlight Cathode
33~38	NC	/	/
39	LED_A	Н	Backlight Anode
40	LED_A	Н	Backlight Anode



E-mail: Helen@kingtechgroup.cn

TEL: 86-755- 23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn



CTP PIN

NO.	Symbol	remark
1	VDD(3.3V)	Power supply
2	VDDD(3.3V)	Power supply
3	GND	Ground
4	GND	Ground
5	VDD(1.8V)	Power supply
6	TP-RESET _(1.8V)	Hardware reset pin
7	TP-SCL(1.8V)	Serial data input pin
8	TP-SDA(1.8V)	Serial data input pin
9	TP-INT (1.8V)	Interrupt pin
10	GND	Ground
11	NC	/
12	NC	/



E-mail: Helen@kingtechgroup.cn TEL: 86-755- 23037763

Mobile: +86-139-2528-0716





8. Backlight:

- 1. Standard Lamp Styles (Edge Lighting Type):
 The LED chips are distributed over the edge light area of the illumination unit, which gives the less power consumption:
- 2. The Main Advantages of the LED Backlight are as following:
 - 2.1 The brightness of the backlight can simply be adjusted. By a resistor or a potentiometer.


3. Data About LED Backlight:


	A Dual 10 out DDD Duckingsit.							
PARAMETER	Sym.	Min.	Тур.	Max.	Unit	Test Condition	Note	
Supply Current	I	-	120		mA	V=30V		
Supply Voltage	V	28		32	V	If=120mA		
Luminous Intensity for LCM(without CTP)	IV	450	500	1	Cd/m ²	If=120mA	2	
Uniformity for LCM	-	70	-	1	%		3	
Life Time	_		30000	-	Hr.		4	
Color				Wh	ite			

NOTE:

- 1. Backlight Only
- 2. Average Luminous Intensity of P1-P9
- 3. Uniformity = Min/Max * 100%
- 4. LED life time defined as follows: The final brightness is at 70% of original brightness

Measured Method: (X*Y: Light Area) Internal Circuit Diagram







E-mail: Helen@kingtechgroup.cn TEL: 86-755- 23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn



9. Packing

TBD



E-mail: Helen@kingtechgroup.cn TEL: 86-755- 23037763

Mobile: +86-139-2528-0716



Web: www.kingtechgroup.cn

10. Standard Specification for Reliability:

10–1. Standard Specifications for Reliability of LCD Module

Item	Description
High temperature operation	The sample should be allowed to stand at 50°C for 96 hours under driving condition and then returning it to normal temperature condition, and allowing it stand for 2 hours.
Low temperature operation	The sample should be allowed to stand at -10° C for 96 hours under driving condition and then returning it to normal temperature condition, and allowing it stand for 2 hours.
High temperature storage	The sample should be allowed to stand at 60°C for 96 hours under no-load condition, and then returning it to normal temperature condition, and allowing it stand for 2 hours.
Low temperature storage	The sample should be allowed to stand at -20°C for 96 hours under no-load condition, then returning it to normal temperature condition, and allowing it stand for 2 hours.
Moisture storage	The sample should be allowed to stand at 50°C±5°C,90%RH MAX for 120 hours under no-load condition, then taking it out and drying it at normal temperature for 2 hours.
Thermal shock storage	-10°C(30min) ~+25°C(5min)~ +60°C(30min) for 10 cycles
Packing vibration	Frequency range: 10Hz ~ 55Hz Amplitude of vibration: 1.5mm X,Y,Z 2 hours for each direction. Sweep time: 12 min
Packing drop test	According to ISTA 1A 2001.
Electrical Static	Air: $\pm 15 \text{KV} 150 \text{pF}/330 \Omega 5 \text{ times}$
Discharge	Contact: $\pm 8KV \ 150pF/330\Omega \ 5$ time
	High temperature operation Low temperature operation High temperature storage Low temperature storage Moisture storage Thermal shock storage Packing vibration Packing drop test

^{*}Sample size for each test item is 3~5pcs





Mobile: +86-139-2528-0716



10 - 2. Testing Conditions and Inspection Criteria

For the final test the testing sample must be stored at room temperature for 24 hours, after the tests listed in Table 10.2, Standard specifications for Reliability have been executed in order to ensure stability.

No	Item	Test Model	In section Criteria
01	Current Consumption	Refer To Specification	The current consumption should conform to the product specification.
02	Contrast	Refer To Specification	After the tests have been executed, the contrast must be larger than half of its initial value prior to the tests.
03	Appearance	Visual inspection	Defect free.

10-3. MTBF

MTBF	Functions, performance, appearance, etc. shall be free from remarkable deterioration within 50,000 hours under ordinary operating and storage conditions room temperature (25 \pm 5 $^{\circ}$ C), normal humidity (50 \pm 10% RH), and in area not exposed to direct sun light.
------	--

E-mail: Helen@kingtechgroup.cn TEL: 86-

TEL: 86-755- 23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn



11. Specification of Quality Assurance:

11-1. Purpose

This standard for Quality Assurance should affirm the quality of LCD module products to supply to purchaser by Kingtech Group Co.,Ltd (Supplier).

11-2. Standard for Quality Test

a. Inspection:

Before delivering, the supplier should take the following tests, and affirm the quality of product.

b. Electro-Optical Characteristics:

According to the individual specification to test the product.

c. Test of Appearance Characteristics:

According to the individual specification to test the product.

d. Test of Reliability Characteristics:

According to the definition of reliability on the specification for testing products.

e. Delivery Test:

Before delivering, the supplier should take the delivery test.

- (i) Test method: According to MIL-STD105E.General Inspection Level II take a single time.
- (ii) The defects classify of AQL as following:

Major defect: AQL = 0.65

Minor defect: AOL = 2.5

Total defects: AQL = 2.5

- 11-3. Non-conforming Analysis & Deal With Manners
 - a. Non-conforming Analysis:
 - (i) Purchaser should supply the detail data of non- conforming sample and the non-conforming.
 - (ii) After accepting the detail data from purchaser, the analysis of non- conforming should be finished in two weeks.
 - (iii) If supplier can not finish analysis on time, must announce purchaser before 3 days.
 - b. Disposition of non- conforming:
 - (i) If find any product defect of supplier during assembly time, supplier must change the good product for every defect after recognition.
 - (ii) Both supplier and customer should analyze the reason and discuss the disposition of non-conforming when the reason of nonconforming is not sure.

11-4. Agreement items

Both sides should discuss together when the following problems happen.

- a. There is any problem of standard of quality assurance, and both sides should think that must be modified.
- b. There is any argument item which does not record in the standard of quality assurance.
- c. Any other special problem.






Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn




11-5. Standard of The Product Appearance Test

- a. Manner of appearance test:
- (i) The test must be under $20W \times 2$ or 40W fluorescent light, and the distance of view must be at 30 ± 5 cm.
 - (ii) When test the model of transmissive product must add the reflective plate.
 - (iii)The test direction is base on around 10° of vertical line.
 - (iiii) Temperature: 25±5°C Humidity: 60±10% RH



(iv) Definition of area:



- A. Area: Viewing area.
- B. Area: Out of viewing area.

(Outside viewing area)

- b. Basic principle:
 - (i) It will accord to the AQL when the standard can not be described.
 - (ii) The sample of the lowest acceptable quality level must be discussed by both supplier and customer when any dispute happened.
 - (iii) Must add new item on time when it is necessary.
 - c. Standard of inspection: (Unit: mm)





E-mail: Helen@kingtechgroup.cn

TEL: 86-755- 23037763

Mobile: +86-139-2528-0716

Web: www.kingtechgroup.cn



11-6. Inspection specification

1.	1-6. Inspection sp	pecification				1
NO	Item			riterion		AQL
01	Electrical Testing	 1.1 Missing vertical, horizontal segment, segment contrast defect. 1.2 Missing character, dot or icon. 1.3 Display malfunction. 1.4 No function or no display. 1.5 Current consumption exceeds product specifications. 1.6 LCD viewing angle defect. 1.7 Mixed product types. 1.8 Flicker 			0.65	
02	Black or White spots or Bright spots or Color spots on LCD (Display only)	 2.1 White and black or color spots on display ≤ 0.25mm, no more than Five spots. 2.2 Densely spaced: No more than three spots within 3mm. 			2.5	
03	LCD and Touch Panel black spots, white spots,	3.1 Round type: As follows: A	more	Size(mm) $Φ \le 0.10$ $0.10 < Φ \le 0.20$ $0.20 < Φ \le 0.25$ $0.25 < Φ \le 0.30$ 0.30 < Φ than two	Acceptable Q'ty Accept no dense 2 2 0 0 o spots within 3mm.	2.5
03	contamination (non – display)	3.2 Line type: (As follows)	Length(mm) L≦3.0 L≦2.5		Acceptable Q'ty Accept no dense 2 Rejection o lines within 3mm.	2.5



E-mail: Helen@kingtechgroup.cn TEL: 86-755- 23037763

37763 **Mobile**: +86-139-2528-0716



Web: www.kingtechgroup.cn

NO	Item	Criterion			AQL
04	Polarizer bubbles	If bubbles are visible, judge using black spot specifications, not easy to find, must check in specify direction	Size Φ(mm) $\Phi \le 0.20$ $0.20 < \Phi \le 0.50$ $0.50 < \Phi \le 1.00$ $1.00 < \Phi$ Total Q'ty	Acceptable Q'ty Accept no dense 3 0 0 3	2.5
05	Scratches	Follow NO.3 -2 Line Type.			
06	Chipped glass	L: Electrode pad length 6.1 General glass chip: 6.1.1 Chip on panel surface ar z: Chip thickness y: Chip $Z \le 1/2t$ Not or $1/2t < z \le 2t$ Not e Unit: mm O If there are 2 or more chips 6.1.2 Corner crack: z: Chip thickness y: Chip Not or Z \subseteq 1/2t Not or Z \subseteq 1/2t Not or Not or Z \subseteq 1/2t Not or Z \sub	s thickness a: LCD side and crack between panels width x : Chip ver viewing area exceed $1/3k$ $x \le 1/3k$	length 1/8a 1/8a o each chip length 1/8a 1/8a o	2.5

-				
	NO	Item	Criterion	AQL



E-mail: Helen@kingtechgroup.cn TE

TEL: 86-755- 23037763

Mobile: +86-139-2528-0716




Symbols:

x: Chip lengthk: Seal widthy: Chip widtht: Glass thicknessa: LCD side length

L: Electrode pad length

7.2 Protrusion over terminal:


7.2.1 Chip on electrode pad:




y: Chip width	x: Chip length	z: Chip thickness
y≦0.5mm	x≤1/8a	$0 < z \le t$

7.2.2 Non-conductive portion:


07 Glass crack





y: Chip width	x: Chip length	z: Chip thickness
y≦L	x≤1/8a	0< z≦t

- ⊙ If there chipped area touches the ITO terminal, over 2/3 of the ITO must remain and be inspected according to electrode terminal specifications.
- If the product will be heat sealed by the customer, the alignment mark must mot be damaged.
- 7.2.3 Substrate protuberance and internal crack



y: width	x: length
$y \le 1/3L$	X≦a

2.5







Mobile: +86-139-2528-0716



Web: www.kingtechgroup.cn

NO	Item	Criterion	AQL
08	Cracked glass	The LCD with extensive crack is not acceptable.	2.5
09	Backlight elements	 9.1 Illumination source flickers when lit. 9.2 Spots or scratches that appear when lit must be judged. Using LCD spot, lines and contamination standards. 9.3 Backlight doesn't light or color is wrong. 	2.5 2.5 0.65
10	Bezel	Bezel must comply with product specifications.	2.5
11	PCB、COB	 11.1 COB seal may not have pinholes larger than 0.2mm or contamination. 11.2 COB seal surface may not have pinholes through to the IC. 11.3 The height of the COB should not exceed the height indicated in the assembly diagram. 11.4 There may not be more than 2mm of sealant outside the seal area on PCB. And there should be no more than three places. 11.5 Parts on PCB must be the same as on the production characteristic chart, There should be no wrong parts, missing parts or excess parts. 11.6 The jumper on the PCB should conform to the product characteristic chart. 	2.5 2.5 2.5 2.5 0.65
12	FPC	12.1 FPC terminal damage \leq 1/2 FPC terminal width and can not affect the function , we judge accept. 12.2 FPC alignment hole damage \leq 1/2 alignment area and can not affect the function , we judge accept.	2.5
13	Soldering	13.1 No cold solder joints, missing solder connections, oxidation or icicle.13.2 No short circuits in components on PCB or FPC.	2.5 0.65






E-mail: Helen@kingtechgroup.cn

TEL: 86-755- 23037763

Mobile: +86-139-2528-0716







NO	Item	Criterion			AQ	ĮL
		Symbols: x: Chip length k: Seal width length L: Electrode pad leng 14.1 General glass ch 14.1.1 Chip on panel	t: Touch Panel Total t			
14	Touch Panel Chipped glass	z: Chip thickness $Z \le t$ mm \odot If there are 2 or m 14.1.2 Corner crack:	y: Chip width ≤ 1/2 k and not over viewing area nore chips, x is the total 1	x: Chip length $x \le 1/8a$ length of each chip	⊙ Unit: 2.5	5
		z: Chip thickness $z \leq t$ mm \odot If there are 2 or m	y: Chip width ≤ 1/2 k and not over viewing area nore chips, x is the total 1	x : Chip length $x \le 1/8a$ length of each chip	⊙ Unit:	







Mobile: +86-139-2528-0716





NO	Item	Criterion	AQL
15	Touch Panel(Fish eye、dent and bubble on film)		2.5
16	Touch Panel Newton ring	Newton ring dimension $\leq 1/2$ touch panel area and not affect font and line distortion($\leq 2.5\%$), it is acceptable.	2.5
17	Touch Panel Linearity	Less than 2.5% is acceptable.	
18	LCD Ripple	Touch the touch panel, can not see the LCD ripple. Pen: R 1.0mm silicon rubber. Operation Force: 80g	2.5
19	General appearance	 19.1 Pin type must match type in specification sheet. 19.2 LCD pin loose or missing pins. 19.3 Product packaging must the same as specified on packaging specification sheet. 19.4 Product dimension and structure must conform to product specification sheet. 	



E-mail: Helen@kingtechgroup.cn TEL: 86-755- 23037763

Mobile: +86-139-2528-0716



Web: www.kingtechgroup.cn

12. Handling Precaution:

12-1 Handling of LCM

- Don't give external shock.
- Don't apply excessive force on the surface.
- Liquid in LCD is hazardous substance. Must not lick and swallow. when the liquid is attach to your hand, skin, cloth etc. Wash it out thoroughly and immediately.
- Don't operate it above the absolute maximum rating.
- Don't disassemble the LCM.
- The operators should be grounded whenever he/she comes into contact with the module. Never touch any of the conductive parts such as the LSI pads, the copper leads on the PCB and the interface terminals with any parts of the human body.
- The modules should be kept in antistatic bags or other containers resistant to static for storage.
- The module is coated with a film to protect the display surface. Be care when peeling off this protective film since static electricity may be generated.

12-2 Storage

- Store in an ambient temperature of 25±10°C, and in a relative humidity of 50±10%RH.
- Don't expose to sunlight or fluorescent light.
 Storage in a clean environment, free from dust, active gas, and solvent.
- Store in anti-static electricity container.
- Store without any physical load.

12-3 Soldering

- Use only soldering irons with proper grounding and no leakage.
- Iron: No higher than 280±10°C and less than 3 sec during Hand soldering.
- Rewiring: no more than 2 times.